



Audio - Visual Station

● Mixing Pre-Amplifier

PAM-998A

Features

- 5 Microphone Input (Mic1 with priority function).
- 3 AUX Input.
- 2 Emergency call Input.
- 2 Output Terminal.
- Individual gain controls for inputs.
- Overall treble and bass control.
- 19" Rack Mount size



Specifications

PAM-998A	
Power Source	220 - 240V , AC 50 / 60 Hz
Power Consumption	30W
Frequency Response	20 to 20,000Hz \pm 3dB
Distortion	Less than 0.5%(Rated Output Power at 1 kHz)
Tone Control	\pm 10dB at 300Hz , 10,000Hz
Input Circuit	
Mic.	2.5mV , 600 Ohms , Unbalanced
AUX	200mV , 10K Ohms , Unbalanced
Line Output	1V 600 Ohms
Muting Function	Reduction of Mic 2-5, Aux 1, 2, 3 Due to Mic. 1 the audio signal supplied from Input Jack
Dimensions (mm)	482(W) X 88(H) X 380(D)
Weight	4kg

* Weight and dimensions indicated above are approximately.

** Specifications are subject to change without notice.