



# Karaoke Mixing Amplifier

KTV-400S

## FEATURES

- 400W x 2 Powerful Output
- 4 Modes Preset EQ ( KTV, MUSIC, CINEMA and MEETING )
- 4 Levels Feedback Control
- Bluetooth Receiver
- Individual 3 Bands EQ for MUSIC and MIC
- Save Mode for New EQ Setting
- Center and SUBWOOFER Output Port
- OPTICAL and COAXIAL Audio Output
- USB and Wifi Ports for PC Control and Upgrade
- Dual Speaker Output Ports (Speakon and Banana Connectors)
- 400 瓦強勁輸出
- 四種預設均衡模式 (KTV, 音樂, 電影和會議)
- 四級反哨叫控制
- 藍牙接收模式
- 三段獨立均衡供音樂和咪高峯
- 可儲存新設定的均衡模式
- 附有中置及超低音輸出口
- 附有光纖和同軸輸出口
- USB 及 wifi 接口與電腦連接供控制和升級之用
- 雙喇叭輸出接口 (專業喇叭插和香蕉插頭)



IR Remote Control

## TECHNICAL SPECIFICATION

	Music	Microphone
Signal and Noise Ratio(SNR)	≥91 db	≥80db
Frequency Response	10HZ-20KHZ/±3.0db	50HZ-20KHZ/±3.0db
Gain	10db±1.0db	26db±1.5db
Total Harmonic Distortion(THD)	≤0.6% output XLR 1Vrms 1 KHz	≤0.8% output XL 1Vrms 1 KHz
Pc Port	USB For Upgrade and Control	
Bluetooth	Yes	
RS-232	Yes	
Size(mm)	430(W) x 360(D) x 100(H)	
Weight	15kg	

\*Weight and dimensions indicated above are approximately. Specifications are subject to change without notice.